APPLICATION FOR
UNITED STATES PATENT
FOR
METHOD AND APPARATUS FOR
DIRECTIONAL RESISTIVITY
MEASUREMENT WHILE DRILLING

Inventors: **Tsili Wang, Houston, Texas**
Leonty Tabarovsky, Houston, Texas
Boris Tchakarov, Houston, Texas
John Signorelli, Houston, Texas
Sheng Fang, Houston, Texas

Assignee: **Baker Hughes, Inc.**

414-28483 US - 2

1

Cross Reference to Related Applications

This patent application claims priority from U.S. Provisional Patent Application serial number 60/408,615 filed on September 6, 2002 entitled Method and Apparatus for the Use of Multicomponent Induction Tool and Cross Component Measurements for
5   Geosteering and Formation Resistivity Data Interpretation in Horizontal Wells" by Tsili Wang, et al. which is incorporated herein by reference in its entirety.

BACKGROUND OF THE INVENTION

10   Field of the Invention

[0001] The invention is related generally to the field of electrical resistivity well logging methods. More specifically, the invention is related to a method and apparatus for providing a transverse coil and measuring cross-component magnetic fields in a downhole resisitivity tool.

15

Description of the Related Art

[0002] Electromagnetic induction and wave propagation logging tools are commonly used for determination of electrical properties of formations surrounding a borehole. These logging tools give measurements of apparent resistivity (or conductivity) of the
20   formation that, when properly interpreted, reasonably determine the petrophysical properties of the formation and the fluids therein.

[0003] The physical principles of electromagnetic induction resistivity well logging are

414-28483 US - 2

2

described, for example, in H.G. Doll, *Introduction to Induction Logging and Application to Logging of Wells Drilled with Oil-Based Mud*, Journal of Petroleum Technology, vol. 1, p.148, Society of Petroleum Engineers, Richardson, Tex. (1949). Many improvements and modifications to electromagnetic induction resistivity instruments

5   have been devised since publication of the Doll reference, supra. Examples of such modifications and improvements can be found, for example, in U.S. Pat. No. 4,837,517; U.S. Pat. No. 5,157,605 issued to *Chandler et al.*; and U.S. Pat. No. 5,452,761 issued to *Beard et al.*

10   **[0004]** A typical electrical resistivity-measuring instrument is an electromagnetic induction military well logging instrument such as described in U.S. Pat. No. 5,452,761 issued to *Beard et al.* The induction logging instrument described in the *Beard* '761 patent includes a number of receiver coils spaced at various axial distances from a transmitter coil. Alternating current is passed through the transmitter coil, which induces

15   alternating electromagnetic fields in the earth formations. Voltages, or measurements, are induced in the receiver coils as a result of electromagnetic induction phenomena related to the alternating electromagnetic fields. A continuous record of the voltages form curves, which are also referred to as induction logs. The induction instruments that are composed of multiple sets of receiver coils are referred to as multi-array induction

20   instruments. Every set of receiver coils together with the transmitter is named as a subarray. Hence, a multi-array induction consists of numerous subarrays and acquires measurements with all the subarrays.

414-28483 US - 2

3

[0005] Conventional induction tools comprising only coaxial transmitter-receiver coil configurations do not have azimuthal sensitivity. Therefore, in a horizontal wellbore, the data do not contain information about directionality of the formation. therefore, It is not possible to distinguish whether a layer is above or below the borehole from these data alone. There is a need to be able to determine directionality of the formation for use in, e.g., geosteering. This directionality knowledge can be obtained using a subset or all of the cross-components of the new multi-component induction tool to allow determination of directionality of the formation.

SUMMARY OF THE INVENTION

[0006] The present invention provides a method and apparatus for measuring cross-component   providing magnetic field in a downhole resistivity tool for traversing a formation well bore measuring a property of interest in a formation adjacent the well bore, the down hole tool having a body with a longitudinal axis substantially aligned with a longitudinal axis of the well bore, the body having an-a external surface and a plurality of grooves cut in the external surface tool body and oriented perpendicular   horizontally with respect to the antenna coil wire. For instance, if aalongitudinal axis of the tool body. A transverse coil whose coil plane contains the longitudinal axis of the tool body is used is used as a transmitter or receiver, the plurality of grooves are provided. An antenna is placed in the grooves for transmission or reception of a transverse magnetic field.

[0007] Directional resistivity measurement while drilling (MWD) provides information on formation's resistivity azimuthal changes around the measuring device mounted close to the drill bit. One application of such measurement is in geosteering in which the azimuthal resistivity information helps determine the location of nearby zones (e.g., water zone or shale layers) relative to the drill bit., of different resistivities. This information helps keep the drill bit inside of target layers, i.e., hydrocarbon pay zones. Commercially available electromagnetic MWD devices (e.g., MPR and EWR) have been used to provide real-time formation resistivity properties for geosteering and formation

414-28483 US - 2

5

evaluation. These tools, however, employ coaxial-coil transmitters and receivers and are

lack of azimuthal resolution. The present invention provides a method and apparatus for

measuring using a cross-component magnetic field in a multicomponent resistivity

logging-while-drilling tool.. in a substantially horizontal borehole. Using data recorded

5   with a single receiver or a plurality of receivers associated with a single transmitter or a

plurality of transmitters with two different transmitter orientations, it is possible to

determine the direction of resistive beds relative to the borehole.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] The invention is best understood by reference to the following figures wherein like numbers refer to like components;

5   FIG. 1 shows a multi-component induction configuration of the invention for horizontal wells;

FIG. 2 shows a configuration for a horizontal well application used to obtain results;

FIG. 3 shows a configuration for a horizontal well application used to obtain results;

FIG. 4 is an illustration of a downhole tool traversing a substantially

10   horizontalhorizontaldeviated borehole in a three layer formation;

FIG. 5 is an illustration of the magnetic field, in-phasephasereal and quadraturequadratureimaginary parts for the ZX transmitter configuration in the three-layer formation shown in Figure 4;

FIG. 6 is an illustration of the arrangement of horizontal grooves cut in tool body or

15   collar to host a transverse coil (X-coil) and vertical grooves used to host a Z-coil;

FIG. 7 is a sectional view of the tool shown in Fig. 6 with wire and ferrite inserted in the gaps between the wire and the bottom of the grooves;

FIG. 8 is a top view of a general groove design showing multiple wires backed by a curved ferrite layer on top of the collar pipe metal;

20   **FIG. 9** is an illustration of the equivalent coil system for the transverse loop shown in **Fig. 7** wherein the small coils all have the same moment direction and therefore their contributions add to each other and the coil size is given by the gap between the wire an

414-28483 US - 2

the groove bottom in **Fig. 7**;

FIG. 10 is an illustration of the magnetic field reception by a transverse coil; and

FIG. 11 is an illustration of an arrangement of dual transmitters and dual receivers.

DESCRIPTION OF EXEMPLARY EMBODIMENT

[0009] Figure 1 shows the configuration of transmitter and receiver coils in a preferred embodiment of the 3DExplorer^{TM} (3DEX) induction logging instrument of Baker Hughes. Three orthogonal transmitters 101, 103, and 105 that are referred to as the T_x, T_z, and T_y transmitters are placed in the order shown. The three transmitters induce magnetic fields in three spatial directions. The subscripts (x, y, z) indicate an orthogonal system substantially defined by the directions of the normals to the transmitters. The z-axis is chosen to be along the longitudinal axis of the tool, while the x-axis and y-axis are mutually perpendicular directions lying in the plane transverse to the axis.

Corresponding to each transmitter 101, 103, and 105 are associated receivers 111, 113, and 115, referred to as the R_x, R_z, and R_y receivers, aligned along the orthogonal system defined by the transmitter normals, placed in the order shown in Figure 1. R_x, R_z, and R_y are responsible for measuring the corresponding magnetic fields H_{xx}, H_{zz}, and H_{yy}. Within this system for naming the magnetic fields, the first index indicates the direction of the transmitter and the second index indicates the direction of the receiver. In addition, the receivers R_y and R_z, measure two cross-components, H_{xy} and H_{xz}, of the magnetic field produced by the T_x transmitter (101). This embodiment of the invention is operable in single frequency or multiple frequency modes.

[0010] Figure 1 shows a sketch of a horizontal configuration for a multi-component induction tool. The orientation of the transmitters and receivers remain fixed with respect to the tool. The multi-component tool in horizontal configuration is sensitive to the .

414-28483 US - 2

9

anisotropic formation, tool location as well as the rotation of the tool around its axis. Only the H_{zz} component is insensitive to tool rotation. In horizontal configuration, the average $0.5*(H_{xx}+H_{yy})$ is independent of tool rotation. The H_{zz} and $0.5*(H_{xx}+H_{yy})$ measurements are dependent on the formation and the tool location and thus an be used

5   to determine the distance from the bed boundaries and for geo-steering the invention.

[0011] The method of the present invention may be used with data acquired with a logging instrument conveyed on a wireline and also with data acquired using a measurements while drilling (MWD) apparatus conveyed on a drilling tubular such as a

10   drill string or coiled tubing. In particular, when used with MWD measurements, this directional information may be used for controlling the direction of drilling and maintaining the position of the borehole relative to beds in the proximity of the borehole.

[0012] Directional resistivity may be measured using cross-component coils. One

15   important cross-component combination is a coaxial (Z) transmitter and an orthogonal (X) receiver. Such a combination has the capability of distinguishing targets located above or below, provided that the targets are within the depth of investigation of the device. This capability tells in which way the drill bit is approaching the geologic target.

20   [0013] The challenge with the cross-component measurement for MWD is in building an X-coil to survive in the hostile drilling environment. The present invention provides a groove design for building an X-coil (used as transmitter or receiver) to meet the

414-28483 US - 2

10

requirement. This design enables the present invention to radiate/detect transverse magnetic fields and protect the X-coil wire from damages posed by drilling operations.

[0014] To illustrate of the directionality of cross-component measurement, **Figure 4** shows the magnetic field measured for a Z-transmitter **1716** and an X-receiver **1714** in a three-layer formation **1709**. The tool **1710** is shown traversing a highly deviated borehole **1730** drilled into the formation **1709**. The upper **1712** and lower **1720** layers are 1 ohm-m and the middle **1718** layer in which the tool **1710** resides is 10 ohm-m. The transmitter **1716** and receiver **1714** are aligned such that the tool axis is parallel to the bed boundaries **1705** and **1707**. As shown in **Figure 3**, observe that the magnetic field (imaginary part) changes sign as the tools moves from the upper layer boundary **1810** to the lower one **1812**. This sign change provides information for distinguishing layers that are above the tool from layers that are below the tool.

[0015] Directional measurement while drilling poses challenge for tool design because of the difficulty in putting a transverse coil. This invention proposes a method for building a transverse coil on a drill collar. The coil detects formation signals and meanwhile stands up to the stress of drilling operation.

[0016] Conceptually, a transverse coil can be built by spreading a wire outside the collar surface on the opposite sides of the collar. The wire is then connected at the ends from inside the collar. To intercept signals there must be a gap between the wire and the collar

414-28483 US - 2

surface at the bottom of the grooves. Because of the damage posed by drilling operations, the wire must be protected by mechanically strong and yet electrically nonconducting material.

5   **[0017] Figure 4** shows a design that meets these two requirements. By analog to the vertical grooves **1912** for hosting a coaxial (Z-) coil, a number of horizontal grooves **1914** are cut on the surface of the collar. The grooves are spread out substantially along the collar axis direction. Holes **1917** are then placed beneath the collar surface **1710** in between the grooves **1914** (**Figure 5**). An electrically insulated wire **1916** is placed

10   through the holes **1917** and grooves **1914**. Within each groove **1914** a small gap **1713** is left between the wire **1916** and the groove bottom **1915**. Ferrite materials **1918** may be filled in the gap, as for a Z-coil design. The wires from the opposite sides are connected to form a loop at the ends.

15   **[0018]** A more general antenna design may use multiple wires **1916** backed by a curved ferrite material **1918** layer on top of the metal pipe wall **1711** (**Figure 6**). Because of its high conductivity, a metal drill collar **1710** is nearly a perfect conductor for operating frequencies from a few hundred kilohertz to a few megahertz. In reaction to an electromagnetic field, the collar will produce surface currents that mute the field inside

20   the collar **1710**. As a result, the physical wire loop produces/receives no fields except in the groove areas **1914**. The effect of the physical wire loop can thus be replaced with small loops **2210**, as shown in **Figure 7**. The areas of the small loops are given by the ·

414-28483 US - 2

12

gaps between the wire **1916** and the groove bottom **1915**. The moments of the small

loops all point the same direction and thus responses add to each other. **Figure 8** sketches

the magnetic field paths **2310** through the grooved area **1923**. For the loop to

radiate/receive fields requires that the grooves have open ends in the direction parallel to

5   the field path. **FIG. 9** is an illustration of the equivalent coil system for the transverse

loop shown in **Fig. 7** wherein the small coils all have the same moment direction and

therefore their contributions add to each other and the coil size is given by the gap

between the wire an the groove bottom in **Fig. 7**. **Figure 10** is an illustration of the

magnetic field reception by a transverse coil; and **Figure 11** is an illustration of an

10   arrangement of dual transmitters and dual receivers.

[0019] Even in the simplest case of two layers separated by a single layer boundary,

determining the azimuth of a nearby layer may require considering four possible different

scenarios: (1) the tool is in a resistive layer overlying a conductive layer, (2) the tool is in

15   a conductive layer overlying a resistive layer, (3) the tool is in a resistive layer underlying

a conductive layer, and (4) the tool in a conductive layer underlying a resistive layer.

Therefore, four independent measurements are made to uniquely distinguish a nearby

layer. This is made possible by measuring both the in-phase and quadrature parts of the

cross-component magnetic field. Measurement of in-phase and quadrature components

20   also help eliminate ambiguity in determining the nearby be azimuth. Table 1 lists the

signature of both parts for the various scenarios.

414-28483 US - 2

Tool position	Formation	Inphase	Quadrature
Tool in upper layer	Conductive layer above resistive layer	+	-
	Resistive layer above conductive layer	-	-
Tool in lower layer	Conductive layer above resistive layer	+	+
	Resistive layer above conductive layer	-	+

Table 1. The in-phase and magnetic field signatures for various tool positions and layer structures.

[0020] The use of the cross-component magnetic field for determination of a nearby

5   layer azimuth relies on the transmitter and receiver coils being orthogonal to each other

so that the direct coupling between the coils is absent. In reality, however, the tool may

be bent due to the borehole curvature or decentralized due to gravity. Tool bending or

eccentricity will destroy the coil orthogonality. In other words, the cross-coil

measurement will contain the directly coupled field that may, depending on the severity

10   of tool bending or eccentricity, destroy the usefulness of the cross-component field for

azimuthal determination. To suppress tool bending or tool eccentricity effect, a second

receiver may be used which is placed in between the first (outer) receiver and the

transmitter. The measured in-phase and quadrature fields from the inner and outer

414-28483 US - 2

14

receivers are then averaged according to the following formula to provide the final measurement

$$H_r = a * H_r^{in} + H_r^{out}$$

$$H_i = a * H_i^{in} + H_i^{out}$$

5   Where H_r^{in} and H_r^{out} are the in-phase measurements of the inner and receivers, respectively, H_i^{in} and H_i^{out} are the quadrature measurements of the two receivers respectively, and a is a coefficient given by $a = -L_{in}^3 / L_{out}^3$, where L_{in}^3 and L_{out}^3 are the distances of the inner and outer receivers to the transmitter, respectively.

10   **[0022]** To make reliable measurements, the gains of the two receivers are known and kept constant. However, downhole temperature variations may cause the gains to change slightly. An uncorrected gain variation may destroy the balancing of the two receiver measurement as expressed by equations (1) and (2). To this end, a second transmitter (Z-directed) may be used which is placed symmetrically with respect to the center and on the

15   opposite side of the two receivers. The measurement from each individual transmitter is then averaged to give the final measurement. The second transmitter also helps to remove a receiver gain drift effect.

[0023] In another embodiment, the method of the present invention is implemented as a set

20   computer executable of instructions on a computer readable medium, comprising ROM,

RAM, CD ROM, Flash or any other computer readable medium, now known or unknown that when executed cause a computer to implement the method of the present invention.

[0024] While the foregoing disclosure is directed to the preferred embodiments of the invention various modifications will be apparent to those skilled in the art. It is intended that all variations within the scope of the appended claims be embraced by the foregoing disclosure. Examples of the more important features of the invention have been summarized rather broadly in order that the detailed description thereof that follows may be better understood, and in order that the contributions to the art may be appreciated. There are, of course, additional features of the invention that will be described hereinafter and which will form the subject of the claims appended hereto.

414-28483 US - 2